


PCTWORLD INTELLECTUAL PROPERTY ORGANIZATION
International Bureau

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁵ : H03D 3/00, 7/16		A1	(11) International Publication Number: WO 94/29948
			(43) International Publication Date: 22 December 1994 (22.12.94)
(21) International Application Number: PCT/IB94/00138		(81) Designated States: CN, JP, KR, US, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 6 June 1994 (06.06.94)			
(30) Priority Data: 9311610.1 4 June 1993 (04.06.93) GB 9408211.2 26 April 1994 (26.04.94) GB			
(71) Applicant (for all designated States except US): RCA THOMSON LICENSING CORPORATION [US/US]; CN 5312, Two Independence Way, Princeton, NJ 08540 (US).		Published With international search report.	
(72) Inventor; and (75) Inventor/Applicant (for US only): ASCHWANDEN, Felix [CH/CH]; Alpenstrasse 29, CH-8800 Thalwil (CH).			
(74) Agents: TRIPOLI, Joseph, S. et al.; GE & RCA Licensing Management Operation, Inc., CN 5312, Princeton, NJ 08540 (US).			

(54) Title: DIRECT CONVERSION TUNER



(57) Abstract

A direct conversion tuner for tuning either analog or digital television signals includes a first and second channels, each having first and second mixers and an intervening filter stage, coupled between an RF input and an output combining unit. The first mixers receive respective first local oscillator signals which have the same frequency but a quadrature phase relationship. The frequency of the first local oscillator signals is controlled according to the selected channel so that it is located within the spectrum of the respective RF signal. The second mixers receive respective second local oscillator signals which have the same frequency but a quadrature phase relationship. The frequency of the second local oscillator signal is located above the passband of the filter stages. A digital gain and phase equalization network is included in one of the channels for adjusting the relative gain and phase shift of the two channels and is automatically controlled by a microcomputer in response to signals sampled at respective points within the first and second channels to reduce the relative gain and phase shift. As a result, near perfect cancellation of unwanted components occurs in the output combining unit.

BEST AVAILABLE COPY

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	GB	United Kingdom	MR	Mauritania
AU	Australia	GE	Georgia	MW	Malawi
BB	Barbados	GN	Guinea	NE	Niger
BE	Belgium	GR	Greece	NL	Netherlands
BF	Burkina Faso	HU	Hungary	NO	Norway
BG	Bulgaria	IE	Ireland	NZ	New Zealand
BJ	Benin	IT	Italy	PL	Poland
BR	Brazil	JP	Japan	PT	Portugal
BY	Belarus	KE	Kenya	RO	Romania
CA	Canada	KG	Kyrgyzstan	RU	Russian Federation
CF	Central African Republic	KP	Democratic People's Republic of Korea	SD	Sudan
CG	Congo	KR	Republic of Korea	SE	Sweden
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LU	Luxembourg	TD	Chad
CS	Czechoslovakia	LV	Latvia	TG	Togo
CZ	Czech Republic	MC	Monaco	TJ	Tajikistan
DE	Germany	MD	Republic of Moldova	TT	Trinidad and Tobago
DK	Denmark	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	US	United States of America
FI	Finland	MN	Mongolia	UZ	Uzbekistan
FR	France			VN	Viet Nam
GA	Gabon				

DIRECT CONVERSION TUNER

Field of the Invention

The invention concerns a so called "direct conversion
5 tuner" which is especially useful in a television receiver.

Background of the Invention

An early type of tuner known as a "tuned radio
frequency tuner" (TRF) included several radio frequency (RF)
10 amplifiers which were all tuned to the frequency of the RF signal
of desired transmission channel followed directly by a detection
section, without an intervening mixer employed in later tuners.
Such a tuner could provide relatively distortion free performance
due to the absence of a mixer. However, TRF tuners tended to be
15 large in size and subject to stability and gain control problems due
to the number RF amplifiers which were needed. Moreover, TRF
tuners did not provide a consistent or adequate degree of signal
selectivity.

The type of tuner which is primarily used today is
20 known as a "heterodyne" or "superheterodyne" tuner. In its
simplest form, known as a "single-conversion" tuner, it comprises
a tunable RF amplifier followed by a frequency conversion stage,
including a mixer and a local oscillator. The frequency conversion
stage produces an intermediate frequency (IF) signal which
25 corresponds to the received RF signal but has a lower frequency.
The IF signal is filtered by an IF filter section and the resultant
signal is coupled to a detection section. The combination of
conversion stage and the following IF filter section provides a
significantly better selectivity characteristic than a TRF tuner.
30 The frequency of the local oscillator signal is offset (usually
higher) from the frequency of the desired RF signal by the desired
frequency of the IF signal. In a television receiver, the local
oscillator signal is controlled so that it places the frequency of the
IF picture carrier corresponding to the RF picture carrier at a
35 nominal frequency, for example, at 45.75 MHz in the United States
and 38.9 MHz in Europe.

A single conversion tuner can be made quite small and
relatively inexpensive. However, it produces unwanted

CONFIRMATION COPY

intermodulation and cross-modulation products due to third and higher order components of the signal transfer characteristics of the mixer included in the frequency conversion stage. Various unwanted conversion products, known in the tuner fields as "image", "one-half IF" and "IF beats", continue to be a problem. The IF filter is designed to minimize unwanted conversion products and also to provide rejection of responses due to adjacent channels (selectivity). Thus, the selection of the IF frequency is a compromise. As a result the rejection of unwanted conversion products and selectivity of the tuner may not be adequate.

The deficiencies of a single conversion tuner have become especially troublesome due to the increasing number of "contiguous" channels now available in large cable television systems. With the advent of digital television transmission systems, such as for high definition television (HDTV), the problem becomes still more difficult because these systems make full use of the available channel spectrum and only a small guard band of a few hundred kilohertz (KHz) exists between channels. In addition, the overall frequency response of a tuner for tuning digital television signals must be flat to the edges of the channel, but nevertheless, have a very steep "roll-off" (attenuation) at the edges for adequate adjacent channel rejection. This makes the design of an appropriate IF filter more complicated since no Nyquist slopes and sound traps, which tend to ease IF filter design, can be used in digital systems. In addition, it is contemplated that both analog and digital television signals will be transmitted during a transition period. In that case, even more adjacent channel selectivity will be required for good reception of the digital signals because digital television signals will be transmitted with much less power than analog television signals.

The "double-conversion" variation of the superheterodyne tuner was developed to overcome the shortcomings of the single-conversion tuner. In this type of tuner, a first conversion stage is followed by a first IF filter section, a second conversion stage, and a second IF filter stage. The first IF section has a very high frequency range, typically in the order of 620 MHz. The second IF section has a much lower frequency

range, typically the same as that of the only IF filter section of a single conversion tuner. The second IF section is followed by a detection section.

5 The very high frequency of the first IF filter section places the RF signals corresponding to unwanted conversion responses such as the "image" response at frequencies readily rejected by tunable RF stages which precede the first conversion stage. The low frequency second IF provides the required adjacent channel selectivity needed for modern television
10 reception. Unfortunately, an double-conversion tuner system requires additional RF and IF circuitry compared to a single conversion tuner, and much of the additional circuitry must function at relatively high frequencies requiring extensive shielding. As a result a double conversion tuner is relatively large
15 in size and expensive.

Another type of tuner known as a "direct conversion" tuner has improved unwanted conversion product rejection and selectivity properties with respect the TRF and heterodyne types of tuners. A direct conversion tuner operates in accordance with a
20 third tuning method in which the frequency of a local oscillator signal of a first frequency conversion stage is set in the middle of the frequency band of the desired channel. The product of the first conversion stage is at relatively low frequency. There are no image responses because the frequency of the first conversion
25 stage is located with the spectrum of the desired RF signal. In addition, the very low frequency range of the signal produced at the output of the first conversion stage makes it possible to readily provide a filter which can reject adjacent channel signals.

Unfortunately, because the first local oscillator signal
30 is centered in the frequency band of the desired channel, both the upper and lower side band of the desired channel will be converted to the frequency range of the first IF signal so that the lower side band (LSB) is in effect folded over onto the upper side band (USB) in the spectrum of the first IF signal. Since the LSB
35 and USB occupy the same frequency range, the LSB and the USB must again be separated before detection. To accomplish this, a direct conversion tuner is arranged as is shown in Figure 1.

Basically, the direct conversion tuner contains two

channels, each with two conversion stages. The received RF signal is coupled to each of two mixers M1A and M1B via a tuned RF amplifier which provides gain and some selectivity. Desirably, the gain of the RF amplifier is automatically controlled in response to an automatic gain control (AGC) signal (not shown). The local oscillator signal generated by a first local oscillator LO1 is tuned to the center frequency ω_0 of the frequency band of the desired channel between the lower side band (LSB) and the upper side band (USB), as is shown in Figure 2a. The first local oscillator signal is split by a phase shifting circuit PS1 into quadrature components that are used to drive mixers M1A and M1B. The respective IF output signals of mixers M1A and M1B are filtered by two low pass filters LPF A and LPF B. Low pass filters LPF A and LPF B provide the necessary selectivity to reject the responses from the adjacent channels and higher order products of mixers M1A and M1B.

Each of the output signals of mixers M1A and M1B includes both a lower side band portion and an upper side band portion corresponding to the LSB and USB portions of the received RF signal. However, as earlier indicated, the LSB portion is folded over so that it is superimposed on the USB portion and occupies the same frequency range, as is shown in Figure 2b. The output signal of low pass filters LPF A and LPF A are coupled to respective ones of a second pair of mixers M2A and M2B. Mixers M2A and M2B are driven by respective ones of a second pair of quadrature local oscillator signals generated by a second local oscillator LO2 and a second phase shifting circuit PS2. Each of the second local oscillator signals has a frequency ω_N located above the cutoff frequency of the low pass filters LPF A and LPF B filters to fulfill the Nyquist criteria. The output signals of mixers M2A and M2B are added in a summer unit SU to produce an output signal which has a spectrum which includes separated lower and upper side band portions, as shown if Figure 2c. This output signal is coupled to a demodulator (not shown) which demodulates it, and the demodulated resultant is coupled to further signal processing sections.

The operation of the direct conversion tuner shown Figure 1 can be mathematically understood by considering a very

simple case in which the received RF signal is assumed to include a sinusoidal upper side band component of $\sin(\omega_0 + \omega_1)$ and a sinusoidal lower side band component of $\sin(\omega_0 - \omega_2)$, as is indicated in Figure 3a. It is also assumed that the gains and phase shifts of the two channels are identical. The phases of the signal components produced at various point of the direct conversion tuner are indicated by the vector arrows in Figure 1. Further, the coefficients of the various mathematical factors corresponding to signal components have been normalized in the following description.

The quadrature first local oscillator signals applied to first mixers M1A and M1B are expressed as $\sin \omega_0$ and $\cos \omega_0$, respectively; and the quadrature second local oscillator signals applied to second mixers M2A and M2B are expressed as $\sin \omega_N$ and $\cos \omega_N$, respectively. The following signal is produced at the output of low pass filter LPF A:

$$\cos \omega_1 + \cos \omega_2$$

The following signal is produced at the output of low pass filter LPF B:

$$\sin \omega_1 - \sin \omega_2$$

The spectra at the outputs of low pass filters LPF A and LPF B are shown in Figure 3b.

The result of the second mixing operation by mixer M2A produces the following output signal:

$$\sin(\omega_N + \omega_1) + \sin(\omega_N - \omega_1) + \sin(\omega_N + \omega_2) + \sin(\omega_N - \omega_2)$$

The result of the second mixing operation by mixer M2B produces the following output signal:

$$\sin(\omega_N + \omega_1) - \sin(\omega_N - \omega_1) - \sin(\omega_N + \omega_2) + \sin(\omega_N - \omega_2)$$

The addition of the two output signals of mixers M2A and M2B by summer SU results in the following signal:

$$\sin(\omega_N + \omega_1) + \sin(\omega_N - \omega_2)$$

The spectrum at the output of summer SU is shown in Figure 3c.

The operation of the direct conversion tuner depends on the cancellation of unwanted components developed in the two channels (compare the output signals of mixers M2A and M2B indicated above including the terms $\sin(\omega_N - \omega_1)$ and $\sin(\omega_N + \omega_2)$). As was stated above, the description of the operation of the direct conversion tuner so far provided assumes

that the gains and phase shifts of corresponding elements of the two channels are identical, resulting in perfect cancellation of the unwanted components after the addition of the output signals of the two channels by summer SU. However, in practice, gain and phase characteristics of the two channels are unequal and change with temperature and time. The gain and phase characteristics affect the phase and magnitude of the vectors shown in Figure 1. As a result, perfect cancellation of the unwanted components no longer occurs causing the generation of unwanted spurious components in the output signal produced by summer SU and the reduction of the quality of the demodulated signal. This is especially the case when the received RF signal is relatively complex, such as a television signal, and does not simply contain a lower and an upper sinusoidal component as assumed in the above description.

The generation of unwanted spurious components when a television signal is tuned by a direct conversion tuner of the type shown in Figure 1 is illustrated in Figures 4a, 4b and 4c. Figure 4a shows the spectrum of a television signal of a single channel. It includes a picture carrier (PIX), a color subcarrier (SC) and a sound carrier (SOUND). The frequency, ω_0 , of the first local oscillator signal is located approximately midway between the picture carrier and the sound carrier. Figure 4b shows the spectrum of the signal resulting from the first mixing operation. Figure 4c shows the spectrum of the output signal of summer SU. For each desired component of the output signal of summer SU to the right of the frequency, ω_N , of the second local oscillator signal, an undesired "companion" to the left exists; and for each desired component of output signal of summer SU to the left of frequency ω_N an undesired "companion" to the right exists. For instance, a "companion" of the picture carrier is present to the right of ω_N between the color subcarrier and the sound carrier. The presence of the unwanted "companions" causes annoying beat patterns in the demodulated video signal and may also adversely affect the demodulated sound signal. Such unwanted components should desirably be suppressed in the order of 45 to 50 dB for optimum performance of the television receiver. This means that the gain and phase errors should desirably be kept less than 0.05 dB. and

0.5 degrees, respectively, for optimum performance of the television receiver. Such performance standards cannot be obtained and maintained with manual adjustments.

5

Summary of the Invention

The present invention concerns an arrangement for automatically reducing the gain and phase difference errors of the two channels of a direct conversion tuner in order to reduce the generation of unwanted components in the output signal. In accordance with an aspect of the invention, a multiple frequency reference signal is inserted as a test signal at respective insertion points of the two channels and signals produced at respective measurement points of the two channels are compared as to amplitude and phase to produce so called "ripple" gain and phase difference responses related to the gain and phase shift differences between two channels, for example, due to the IF low pass filters. In accordance with another aspect of the invention, the signals developed at the measurement points in response to the RF signal for the selected channel are also compared as to amplitude and phase to produce so called "DC" gain and phase difference values related to gain and phase shift differences of one or more of the conversion stages. The "ripple" gain and phase responses and the "DC" gain and phase difference values are used to control a gain and phase correction network so that the amplitude and phase differences between the measured signals of the two channels are reduced. Preferably, the arrangement is implemented in a digital embodiment in which analog-to digital converters are included in respective ones of the channels after the first conversion stages and the gain and phase correction units comprise digital filters after the second conversion stages. The operation of automatic gain and phase equalization arrangement can be automatically initiated each time the television receiver is switched on or a new channel is selected.

These and other aspects of the invention will be described with respect to the accompanying Drawing.

Brief Description of the Drawing

In the Drawing, Figures 1, 2a-2c, 3a-3c and 4a-4c concern the background of the invention and have previously been described. Briefly:

5 Figure 1 is a block diagram of a direct conversion tuner as is known in the prior art;

 Figures 2a, 2b and 2c are graphical representations of the spectra of signals at various points of the direct conversion tuner shown in Figure 1;

10 Figures 3a, 3b and 3c are graphical representations of the spectra of signals at various points of the direct conversion tuner shown in Figure 1 assuming that the input signal consists of two sinusoidal components; and

 Figures 4a, 4b and 4c are graphical representations of
15 the spectra of signals at various points of the direct conversion tuner shown in Figure 1 when the input signal comprises an analog television signal.

 The remaining Figures of the Drawing concern the embodiment of the invention. Briefly:

20 Figure 5 is a block diagram of a direct conversion tuner including an automatic gain and phase equalization arrangement constructed in accordance with an aspect of the invention;

 Figure 6 is a vector diagram useful in understanding
25 how gain and phase errors are measured by the automatic gain and phase equalization arrangement;

 Figures 7a and 7b, 8a and 8b, and 9a and 9b are graphical representations of spectra of phase and gain errors useful in understanding how phase and gain correction
30 information used by the automatic gain and phase equalization arrangement is obtained;

 Figure 10 is a vector diagram also useful in understanding how phase and gain correction information used by the automatic gain and phase equalization arrangement is
35 obtained;

 Figures 11a and 11b are graphical representations of spectra of phase and gain correction responses needed for phase

and gain equalization which result from the operations illustrated in Figures 7a and 7b, 8a and 8b, 9a and 9b and 10;

Figure 12 is a flow chart indicating the overall operation of the automatic gain and phase equalization arrangement.

Detailed Description of the Drawing

The direct conversion tuner shown in Figure 5 is generally similar to the one shown in Figure 1, but includes additional elements which comprise an automatic gain and phase equalization arrangement constructed in accordance with an aspect of the invention and certain related elements. Those elements of the direct conversion tuner shown in Figure 5 which have the same or similar functions as corresponding elements of the direct conversion tuner shown in Figure 1 are identified by the same or similar reference designations and will not be described in details again.

The automatic gain and phase equalization arrangement comprises a gain and phase correction network including a first gain control unit labeled GC and a second gain control unit which is actually used for phase correction and is therefore labeled PC. The gain and phase correction network is inserted in channel A between LPF A and output summer SU2. Gain correction unit GC and phase correction unit PC comprise respective programmable digital filters which are controlled by a microcomputer MC to adjust the gain and phase characteristics of channel A so that the gain and phase characteristics of the channels A and B are substantially identical. Gain correction unit GC and phase correction unit PC may, for example comprise, finite impulse response (FIR) filters. Microcomputer MC samples the signals developed at points A and B just before second mixers M2A and M2B in response to a test signal and determines the relative amplitudes and phases of the sampled signals to develop filter coefficient control signals for gain correction unit GC and phase correction unit PC. For this purpose, microcomputer MC generates a reference signal labeled ω_{REF} which is inserted as a test signal just after first mixers M1A and M1B, for example, via resistors RA and RB. Microcomputer MC also samples the signals

developed at points A and B in response to the received RF signal for the selected channel and determines the relative amplitudes and phases of the sampled signals to develop the filter coefficient control signals. The generation of the filter coefficient control signals will be described in detail below. Microcomputer may comprise the same microcomputer which is used to control other functions of the television receiver.

In the embodiment of invention shown in Figure 5, the gain and phase correction is accomplished by the addition of two signals which are in quadrature phase relationship as will be described below in greater detail with respect to the vector diagram shown in Figure 10. For this purpose gain correction unit GC and phase correction unit PC (which is actually another gain control unit) are included in separate paths for which the respective signals are in quadrature phase relationship. More specifically, gain correction unit GC receives a signal developed at a point C at the output of second mixer M2A while phase correction unit PC receives a signal developed at a point F at the output of an additional mixer M3. The same local oscillator signal which is coupled to second mixer M2B of channel B is coupled to additional mixer M3 so that oscillator signals coupled to mixers M2A and M3 have a quadrature phase relationship ($\sin \omega_N$ and $\cos \omega_N$, respectively). As a result, the signals developed at points C and F have a quadrature phase relationship. The output signal of gain control unit GC developed at a point C' is added to the output signal of phase correction unit PC developed at a point F' by an additional summer unit SU2. The signal produced at a point G at the output of additional summer unit SU2 is combined with to the signal produced at a point D at the output of a mixer M2B by a summer unit SU1 corresponding to summer unit SU of the direct conversion tuner shown in Figure 1. The signal developed at a point E at the output of summer SU1 is coupled to a demodulator section (not shown).

Since the gain and phase equalization apparatus is implemented in digital form in the direct conversion tuner shown in Figure 5, analog-to-digital converters ADC A and ADC B have been added to respective ones of channels A and B prior to the second conversion stages. The ADC A and ADC B receive amplified

versions of the output signals of LPF A and LPF B from respective ones of amplifiers AMP A and AMP B and provide respective digital versions of the output signals of LPF A and LPF B. The outputs of amplifiers AMP A and AMP B are capacitively coupled to the inputs of the ADC A and ADC B via respective ones of capacitors CA and CB to avoid DC drift problems. The amplifiers may be omitted when the outputs signals of LPF A and LPF B have sufficient amplitudes to permit reliable analog-to-digital conversion. In the direct conversion tuner shown in Figure 5, second mixers M2A and M2B comprise digital multipliers instead of analog mixers and summers SU1 and SU2 are digital adders.

Before describing the gain and phase equalization operation in detail it is helpful to describe the nature of the gain and phase errors. The gain and phase errors can be divided into "ripple" and "DC" errors. The "ripple" error is caused by the differences between the gain and phase responses of low pass filters LPF A and LPF B. It varies as a function of the IF frequency, but is constant for all received television channels. The "DC" error is caused by quadrature errors and gain differences between first mixers M1A and M2B. It is constant for a selected channel but varies with the frequency of the first local oscillator. Second mixers M2A and M2B do not introduce additional errors if they are implemented in digital form as is the case in the direct conversion tuner shown in Figure 5.

There is an additional error which can be referred to as an "asymmetry" error which occurs when first mixers M1A and M1B are implemented as a doubly-balanced mixer. The use of a doubly-balanced mixer is desirable since it tends to reduce the coupling of the RF signal and local oscillator signal to the output of the mixer because of its balanced configuration. However, a doubly balanced mixer is not perfectly balanced and this results in slightly different gain and phase characteristics for RF signal components which have a frequency below the frequency, ω_0 , of the first local oscillator signal than for RF signal components which have a frequency above the frequency of the first local oscillator signal. The "asymmetry" error is small and can be neglected in most cases. However, it can be corrected, if desired, as will be described below.

It is possible to measure gain and phase errors with the use of a "sweep" generator which is connected to the antenna input, and which "sweeps" the frequency range of a selected channel. This method is relatively complicated and expensive.

5 Measuring the ripple and DC errors separately is simpler.

The ripple error can be measured by using a multiple frequency reference signal, labeled ω_{REF} in Figure 5. The reference signal has a low frequency range which only needs to be sufficiently broad to cover the IF frequency range. Experiments
10 have shown that eight to ten discrete test frequencies are sufficient to obtain satisfactory results. The reference signal may be generated by an oscillator (not shown) under the control of microcomputer MC or directly by microcomputer MC by using a look-up table. During the ripple error test, the tuner has to be
15 disabled from responding to the received RF signal. This may be accomplished by turning off the first local oscillator (LO1) or disabling the RF stage. The ripple errors can be measured each time the television is switched on or when a new channel is selected. Once the ripple errors have been measured, the normal
20 operation of the tuner is again initiated.

The DC errors of mixers M1A and M1B are local oscillator or channel-dependent, but are otherwise constant over the frequency range of each channel. Therefore, the DC errors can be measured using a single frequency test signal for each selected
25 channel. However, advantageously, the picture and sound carriers of the received television signal can be used to measure the DC errors. Both carriers are known in frequency and have high energy which makes the measurement reliable. Using both the picture and sound carriers allows for the correction of the
30 asymmetry errors because, as shown in Figure 4a, the frequency of the picture carrier is below the frequency, ω_0 , of the first local oscillator signal and the frequency of the sound carrier is above the frequency of the first local oscillator signal. The carriers are measured at points A and B at the outputs of ADC A and ADC B
35 during the occurrence of the broad vertical equalizing pulses when the picture carrier has its highest energy but is not modulated with video information. However, because both picture and sound carriers are present, the carriers need to be

separated. The separation can be accomplished after the measurement by microcomputer MC in accordance with a software filter program. For example, low pass and high pass filter responses can be obtained utilizing a MatLab™ program commercially available from MATHWORKS, Inc., of Massachusetts. The low and high pass filter responses can be used to separate the picture carrier and sound carrier responsive portions of the measurement values. Alternatively, microcomputer MC may comprise a digital signal processor (DSP) unit including digital filters and a microprocessor may advantageously be used. In that case, the digital filters can be used to separate the picture and sound carriers.

The phase error for a particular test can be calculated by considering the vectors "a" and "b" representing the digitized signals measured at points A and B and the vector "c" representing their differences as the three sides of a triangle, as is shown in Figure 6, and by using the geometric cosine law to find the angle γ between vectors "a" and "b". The gain error is the ratio of the magnitudes of vectors "a" and "b". This is valid only for RMS (root mean square) values so that a number of samples is required. More specifically, for each sample, the signal levels (A and B) at points A and B are measured and squared (A^2 and B^2) by microcomputer MC. In addition, for each sample, the difference between the signal levels ($A - B$) at points A and B is calculated and squared ($(A - B)^2$). The squared values for all of the samples are added. The squared magnitude of third side "c" of the triangle is related to the sum of the squared values of the difference values ($\sum(A - B)^2$). The square root of the ratio of the sums of the squared signal values ($(\sum A^2 / \sum B^2)^{1/2}$) is proportional to the relative gains of the two channels. The cosine law equation indicated in Figure 6 is used to calculate the relative phase angle g from the appropriate sums of squared values. A relatively large number of samples, for example, in the order of 500 or more, because the magnitudes of the signals measured at points A and B are continuously changing, especially during the DC and asymmetry error measurements when the measured signals are responsive to the carriers of the received RF signal. This method provides sufficient accuracy in an eight-bit environment.

The use of the cosine law in the above described manner does not result in reliable results for very small phase difference angles. The problem is solved in software by means of the addition of a phase shift to one of the signals measures at points A and B. The phase shift is latter subtracted from the
5 calculated phase difference.

Once the gain and phase error values have been measured and stored in microcomputer MC, the necessary coefficients for the correction filters can be calculated. Figures 7a
10 and 7b show examples of measured ripple phase and gain errors for one half of the received spectrum. The phase and gain errors for the other half of the spectrum are obtained by forming the mirror image of the existing phase error about the zero point and the mirror image of the existing gain error about the vertical axis.
15 The resulting full spectra of the ripple phase and gain errors are shown in Figures 8a and 8b.

The ripple phase and gain error responses have to be combined with the DC phase and gain error responses. More specifically, the DC phase error is added to the ripple phase error
20 response shown in Figure 8a. The DC gain error is used to multiply the ripple gain error response shown in Figure 8b.

If asymmetry errors exists, they can be compensated by using the asymmetry errors measured by using the picture and sound carriers, as earlier indicated. More specifically, the
25 asymmetry phase error for the picture carrier is added to the left side of the ripple phase error response shown in Figure 8a and the asymmetry phase error for the sound carrier is added to the right side. The asymmetry gain error for the picture carrier is used to multiply the left side of the ripple gain error response shown in
30 Figure 8b and the asymmetry gain error for the sound carrier is used to multiply the right side. As a result of the combination of the asymmetry errors with the ripple errors, a step in the middle of the responses may occur. In many cases the asymmetry errors are small and can be ignored, and therefore only the response to
35 the picture carrier is needed. In the present example, it is assumed that the asymmetry errors are small, and therefor, have been ignored.

The final phase and gain error responses are shown in Figures 9a and 9b. The phase and gain error responses shown in Figures 9a and 9b cannot by themselves be used for calculating the error correction filter coefficients for gain correction unit GC and phase correction unit PC. Rather, the responses shown in Figures 9a and 9b have to be converted to the phase and gain correction responses shown in Figures 11a and 11b frequency point by frequency point. The manner in which this is accomplished is illustrated by the vector diagram shown in Figure 10. In Figure 10, the vectors correspond to signals developed at respectively labeled points of the direct conversion tuner shown in Figure 5. With reference to Figure 10, the phase (d) and gain errors at each frequency point of the response shown in Figures 9a and 9b are used to calculate a coefficient for changing the magnitude of vector C and coefficient for changing the magnitude of a quadrature vector F so that when the resultant vectors C' and F' are combined, vector G is formed which is equal in magnitude but opposite in phase to vector D, and therefor results in cancellation when added to vector D. The desired phase and gain correction compensation responses shown in Figures 11a and 11b correspond to the multiplication factors for vectors C and F required to produce vectors C' and F' for each sampled frequency on the frequency axis. The responses shown in Figures 11a and 11b are not symmetrical due to interaction between gain and phase.

The coefficients for phase correction unit PC and gain correction unit GC can be computed from the responses shown in Figure 11a and 11b using the MatLab™ FIR2 program. It should be noted that the coefficients for frequencies below second local oscillator frequency ω_N and the ones needed for frequencies above second local oscillator frequency ω_N correspond respectively to the opposite sides of the responses shown in Figures 11a and 11b because the inverse positional relationship between the desired components and the undesired components. This factor is easily incorporated in the hardware by inverting the signal developed at point D as is indicated by inverter I as shown in Figure 5, or by subtracting the signal developed at point D from the signal developed at point G.

Once the filter coefficients for the selected channel have been calculated they are stored for retrieval whenever the same channel is again selected. As a result, the receiver is ready for reception when a new channel is selected without first
5 calculating "new" filter coefficients. Temperature affects the drift of components, such as inductors and capacitors, in the IF filter and therefor affects the gain and phase error responses. However, it has been found that it is not necessary to perform the ripple gain and phase error measurements other than when the receiver
10 is first turned on or perhaps when a new channel is initially selected. Accordingly, it is not necessary to interrupt the reception of a program. Measurement of the DC gain and phase errors is not a problem because the received television signal can be continuously monitored without affecting the normal operation
15 of the tuner.

It has been found that the location of the frequency, ω_0 , of the first local oscillator signals within the spectrum of the RF signal can be used to optimize the operation of the direct conversion tuner. For example, the frequency of the first local
20 oscillator signals should desirably be between 1.7 and 2 MHz above the picture carrier (see Figure 4a) for NTSC television signals, and between 2 and 2.8 MHz above the picture carrier for PAL television signals. The frequency of the first local oscillator signals can be set in accordance with the channel number, for
25 example, by a phase locked loop tuning control system (sometimes called a "frequency synthesizer"). In that case, microcomputer MC may be used to control the frequency of the frequency determining programmable divider of the phase locked loop. An automatic fine tuning (AFT) arrangement responsive to the
30 frequency of the picture carrier may be used to maintain the frequency of the first local oscillator signals at the desired frequency. The frequency of the picture carrier may be measured by microcomputer MC during the DC error measurement operation when the signals developed at points A and B are sampled.

35 The direct conversion tuner shown in Figure 1 has been described so far with respect to tuning of analog television signals in which picture, sound and color subcarrier signals are modulated on RF carriers in accordance with a conventional

television standard such as NTSC, PAL or SECAM. However the direct conversion tuner is also useful, and may in fact be even more useful, for tuning digital television signals, such as HDTV (high definition television) signals. As earlier noted, HDTV systems make full use of the available channel spectrum, have only a small guard band of a few hundred kilohertz (KHz) between channels, and require a tuner response which is flat to the channel edges but which is very steep at the edges for adequate adjacent channel rejection. A direct conversion tuner is particularly well suited to such a HDTV environment because it has a low IF frequency range which allows the use of simple and effective filters. An IF filter with a sharp "cutoff" and a large "stop-band" region is much easier to obtain at low frequencies than at the conventional IF frequencies (38 MHz and higher).

While the direct conversion tuner described so far is well suited for tuning digital television signals, certain modifications need to be incorporated because discrete carriers which can be used to measure the DC gain and phase errors are usually not transmitted in a digital television system. However, it has been found that the spectra of digital television signals, which are typically flat and have similarities to random noise, may be used to accurately measure the DC errors. The use of the spectra of the digital television signals to measure the DC errors may require more samples to be used than when picture or sound carriers are used. For example, samples taken over ten to twenty television lines may be required. In a direct conversion tuner for tuning digital television signals, the same method of measuring the ripple gain and phase errors using a plural frequency reference signal previously described with respect to the direct conversion tuner for tuning analog television signals is used.

Even if the spectra of the received digital television signals are not flat for a particular digital television system, the spectra can still be used to measure the DC gain and phase difference errors, provided that the shape of the spectra is to modify filter coefficients.

Digital television signals are more robust than analog television signals and therefore the generation of unwanted spurious frequency components is less critical. It is therefore not

necessary to consider the small asymmetric errors and larger tolerances for gain and phase errors can be accepted.

In a television receiver which is capable of processing both analog television signals and digital television signals, a single direct conversion tuner may be used to tune both the analog and digital television signals. The flow chart shown in Figure 12 summarizes the operation of the direct conversion tuner which has been previously described, and additionally indicates its operation in a dual mode television receiver. As is indicated in the flow chart, after the receiver has been energized or a desired channel is selected, the previously stored gain and phase equalization data for the selected channel is retrieved from memory and coupled to gain correction unit GC and phase correction unit PC, the ripple error measurements are made. Thereafter, the detection of the presence or absence of a picture carrier causes the selection of either an analog television signal branch or a digital television signal branch, respectively, of the program for measuring the DC errors and calculating the filter coefficients.

While the invention has been described in terms of as specific embodiment, it is contemplated that modifications will occur to those skilled in the art. For example while individual gain and phase correction units are utilized in the embodiment, a single digital filter may be provided to provide both gain correction and phase correction. Such a filter may be constructed in either FIR (finite impulse response) or IIR (infinite impulse response) form. In addition, while gain correction unit GC and phase correction unit PC are included in the same channel in the embodiment, one of the units may be included in one channel and the other may be included in the other channel. Further, while two analog-to-digital converter are utilized in the embodiment, it is possible to use a single ADC which is multiplexed to sample the signals developed at the measurement points of the two channels. Still further, while the use of the picture and sound carriers has been described with respect to the DC and asymmetry error measurements in a direct conversion tuner for tuning analog television signals, other components may also be utilized. For example, the color subcarrier may be used in place of sound

carrier in the asymmetry error measurement. Even still further, while the reference signal is inserted after the first mixers in the embodiment, the reference signal can be inserted at other locations such as in the RF stage. In the same vain, while the measurement points of the embodiment are located before the second mixers because the second mixers are implemented in digital form, different measurement points, such as ones located after the second mixers, may be used. Moreover, while a direct conversion tuner including the automatic gain and phase equalization provisions which have been described is particularly well suited for tuning television signals, it is also useful for tuning other types of communications signals. These and other modifications are intended to be within the scope of the following claims.

Claims

1. In a receiver, tuning apparatus for tuning a selected one of a plurality of RF signals receivers at an RF input to
5 produce an output signal at an output, comprising:

first and second channels each having an input and an output and, in the order named, a first mixer stage, a filter stage and a second mixer stage coupled between said input and output;

10 said inputs of said first and second channels being coupled to said RF input;

a summing unit having first and second inputs and an output, said outputs of said first and second channels being coupled to respective inputs of a summing network, and said output of said summing unit being coupled to the output of said
15 tuning apparatus;

means for providing first local oscillator signals of the same frequency but of quadrature phases to respective ones of said first mixer stages; said the frequency of said first local oscillator signals being located within the frequency spectrum of
20 said selected RF signal;

means for providing second local oscillator signals of the same frequency but of quadrature phases to respective ones of said second mixer stages; said the frequency of said first local oscillator signals being located above the passbands of the
25 respective said filter stages;

means for monitoring first and second signals produced at respective points within said first and second channels;

30 means for adjusting the relative gain and the phase shift of said first and second channels; and

means for automatically controlling said gain and phase shift adjusting means to reduce the differences between the relative amplitudes and the phases of said first and second channels in response to the relative amplitudes and phases of said
35 first and second signals.

2. The tuning apparatus recited in claim 1, wherein:
said automatic controlling means includes means for
generating a reference signal and inserting it into each of said first
and second channels and for controlling said gain and phase shift
5 adjusting means in response to said first and second signals as
affected by said reference signal.

3. The tuning apparatus recited in claim 2, wherein:
said reference signal has a plurality of frequencies,
10 and said automatic controlling means is responsive to said first
and second signals as affected by said reference signal at each of
said pluralities of said frequencies.

4. The tuning apparatus recited in claim 1, wherein:
15 said automatic controlling means is responsive to said
first and second signals as affected by said selected RF signal.

5. The tuning apparatus recited in claim 4, wherein:
said selected RF signal is an analog television signal
20 including at least one carrier, and said automatic controlling
means is responsive to said first and second signals as affected by
said one carrier.

6. The tuning apparatus recited in claim 4, wherein:
25 said selected RF signal is an analog television signal
including a picture and a sound carrier, and said automatic
controlling means is responsive to said first and second signals as
affected by at least one of said picture and sound carriers.

7. The tuning apparatus recited in claim 6, wherein:
30 said automatic controlling means is responsive to said
first and second signals as affected by each one of said picture and
sound carriers.

8. The tuning apparatus recited in claim 4, wherein:
said selected RF signal is a digital television signal and
said automatic controlling means is responsive to said first and
second signals as affected by the spectrum of said digital
5 television signal.

9. The tuning apparatus recited in claim 1, wherein:
said automatic controlling means includes means for
generating a reference signal and inserting it into each of said first
10 and second channels and for controlling said gain and phase shift
adjusting means in response to said first and second signals as
affected by said reference signal; and said automatic controlling
means is also responsive to said first and second signals as
affected by said selected RF signal.

15
10. The tuning apparatus recited in claim 9, wherein:
said reference signal has a plurality of frequencies,
and said automatic controlling means is responsive to said first
and second signals as affected by said reference signal at each one
20 of said pluralities of said reference signal.

11. The tuning apparatus recited in claim 1, wherein:
said gain adjusting means and phase shift adjusting
means comprise respective individual units.

25
12. The tuning apparatus recited in claim 11, wherein:
said gain adjusting means and said phase shift
adjusting means are included in the same one of said channels.

13. The tuning apparatus recited in claim 12, wherein:
said gain adjusting means is coupled in cascade with
an additional summing network between said second mixer and
said output of said one channel; and

5 said phase shift adjusting means comprises an
additional mixer and an additional gain adjusting means coupled
in cascade between said filter stage and said output of said one
channel; said additional mixer receiving a signal having the same
frequency as the frequency of said second local oscillator signal of
10 said one channel but of quadrature phase.

14. The tuning apparatus recited in claim 1, wherein:
said means for monitoring said first and second signals
includes an analog-to-digital converter; and

15 means for automatically controlling said gain and
phase shift adjusting means includes a microcontroller operating
under program control and is coupled to said analog-to-digital
converter.

20 15. The tuning apparatus recited in claim 14, wherein:
said means for monitoring said first and second signals
includes first and second analog-to-digital converters included in
respective ones of said first and second channels; and

25 said means for adjusting the relative gains and the
phase shifts of said first and second channels includes a digital
filter.

16. The tuning apparatus recited in claim 14, wherein
said first and second digital-to-analog converters are
30 coupled between respective ones of said filters and said second
mixers of said first and second channels; and

 said second mixers of respective ones of said first and
second channels are digital mixers.

17. The tuning apparatus recited in claim 16, wherein:
said automatic controlling means includes means for
generating a reference signal and inserting it into each of said first
and second channels after respective ones of said first and second
5 mixers.

18. The tuning apparatus recited in claim 1, wherein:
said automatic controlling means is responsive to said
first and second signals as affected by said selected RF signal;
10 said selected RF signal may be either an analog
television signal including a carrier, or a digital television signal;
said automatic controlling means is responsive to said
first and second signals as affected by said picture carrier during
ones of said synchronization components when said selected RF
15 signal is said analog television signal; and
said automatic controlling means is responsive to said
first and second signals as affected by the spectrum of said digital
television signal when said selected RF signal is said digital
television signal.

19. The tuning apparatus recited in claim 18, wherein:
said automatic controlling means is responsive to the
presence or absence of said carrier to determine whether said
selected RF signal is said analog television signal or said digital
25 television signal.




FIG. 1
PRIOR ART




FIG. 2a




FIG. 2b




FIG. 2c




FIG. 3a




FIG. 3b




FIG. 3c




FIG. 4a




FIG. 4b




FIG. 4c




FIG. 5




FIG. 6




FIG. 10

FIG. 7a




FIG. 7b




FIG. 8a




FIG. 8b




FIG. 9a




FIG. 9b




FIG. 11a





FIG. 11b






FIG. 12

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/IB 94/00138

A. CLASSIFICATION OF SUBJECT MATTER
 IPC 5 H03D3/00 H03D7/16

According to International Patent Classification (IPC) or to both national classification and IPC:

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 5 H03D

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US,A,4 944 025 (GEHRING ET AL.) 24 July 1990 see the whole document ---	1
A	EP,A,0 343 273 (DEUTSCHE ITT INDUSTRIES GMBH) 29 November 1989 see abstract; figure 7 ---	1
A	EP,A,0 496 621 (ROCKWELL INTERNATIONAL CORPORATION) 29 July 1992 see the whole document -----	1

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

- "I" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- "&" document member of the same patent family

Date of the actual completion of the international search

22 August 1994

Date of mailing of the international search report

12.09.94

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
 NL - 2280 HV Rijswijk
 Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
 Fax: (+31-70) 340-3016

Authorized officer

Peeters, M

INTERNATIONAL SEARCH REPORT

information on patent family members

International Application No.

PCT/IB 94/00138

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US-A-4944025	24-07-90	NONE	
EP-A-0343273	29-11-89	CN-A- 1038737	10-01-90
		DE-D- 3889326	01-06-94
		JP-A- 2030237	31-01-90
		US-A- 4926443	15-05-90
EP-A-0496621	29-07-92	US-A- 5230099	20-07-93

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.